



MF2

Pierścień montażowy

wymiary

Typ	$\varnothing D$ [mm]	$\varnothing D_k$ [mm]	E [mm]	E_1 [mm]	$\varnothing D_m$ [mm]	$\varnothing d_1$ [mm]	H_6 [mm]
MF/MF2 400	400	438	340	280	560	10	320
MF/MF2 450	450	487	360	320	600	10	340
MF/MF2 500	500	541	400	350	680	12	370
MF/MF2 560	560	605	440	390	760	12	400
MF/MF2 630	630	674	500	440	860	14	430
MF/MF2 710	710	751	600	540	940	14	480
MF/MF2 800	800	837	650	580	1040	14	530
MF/MF2 900	900	958	700	630	1200	16	580
MF/MF21000	1000	1067	800	720	1300	16	680
MF/MF2 1120	1120	1200	900	820	1440	16	740
MF/MF2 1250	1250	1337	1000	920	1600	16	800
MF/MF2 1400	1400	1491	1100	980	1770	20	880
MF/MF2 1600	1600	1663	1260	1140	1950	2	980

